

First edition
2013-07-01

AMENDMENT 1
2017-04

**Intelligent transport systems —
Communications access for land
mobiles (CALM) — ITS station
management —**

Part 5:

**Fast service advertisement protocol
(FSAP)**

AMENDMENT 1

*Systèmes intelligents de transport — Accès aux communications des
services mobiles terrestres (CALM) — Gestion des stations ITS —*

Partie 5: Protocole d'avertissement de service rapide (FSAP)

AMENDEMENT 1



Reference number
ISO 24102-5:2013/Amd.1:2017(E)

© ISO 2017

STANDARDSISO.COM : Click to view the full PDF of ISO 24102-5:2013/Amd 1:2017



COPYRIGHT PROTECTED DOCUMENT

© ISO 2017, Published in Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Ch. de Blandonnet 8 • CP 401
CH-1214 Vernier, Geneva, Switzerland
Tel. +41 22 749 01 11
Fax +41 22 749 09 47
copyright@iso.org
www.iso.org

Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular the different approval criteria needed for the different types of ISO documents should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see www.iso.org/directives).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation on the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT) see the following URL: www.iso.org/iso/foreword.html.

Amendment 1 to ISO 24102-5:2013 was prepared by Technical Committee ISO/TC 204, *Intelligent transport systems*.

A list of all parts in the ISO 24102 series can be found on the ISO website.

STANDARDSISO.COM : Click to view the full PDF of ISO 24102-5:2013/Amd 1:2017

Intelligent transport systems — Communications access for land mobiles (CALM) — ITS station management —

Part 5: Fast service advertisement protocol (FSAP)

AMENDMENT 1

Page 13, 8.2.1

Replace the bullet line: “- non-IP based services (timeout information), or” with the bullet line: “- non-IP based services, or”.

Page 14, 8.2.4

Insert the following Note at the end of the first paragraph:

NOTE The groupcast manager may use predetermined quantized values of the interval between subsequent transmissions of the service advertisement message that match best the requested interval.

Page 19, Annex A

Replace the entire Annex A with the following one:

Annex A (normative)

ASN.1 modules

A.1 Overview

The following ASN.1 module is specified in this annex:

— CALMfsap { ISO.(1) standard (0) calm-management (24102) fsap (5) asnm-1 (1)}

NOTE The acronym “CALM” used in this annex was introduced in the previous edition of this document. For backward-compatibility, the acronym is maintained here.

A.2 Module CALMfsap

This module specifies ASN.1 type definitions together with useful ASN.1 value definitions.

Unaligned packed encoding rules (PER) as specified in ISO/IEC 8825-2 shall be applied for this ASN.1 module.

In order to achieve octet alignment enabling cheap implementations, “fill” bits were defined. All fill bits shall be set to the value ‘0’b.

```
CALMfsap { iso (1) standard (0) calm-management (24102) fsap (5) asnm-1 (1) }
```

```
DEFINITIONS AUTOMATIC TAGS ::= BEGIN
```

```
IMPORTS
```

```
ITSaid FROM CITSapplMgmtApplReg { iso(1) standard(0) cits-applMgmt (17419) applRegistry
```

```

(2)}

PortNumber FROM CALMfntp { iso (1) standard (0) calm-nonip(29281) fntp(1) asnm-1 (1)}

Directivity, LLserviceAddr, MedType, UserPriority FROM CALMllsap {iso(1) standard(0) calm-
ll-sap(21218) asnm-1 (1)}

ApplicationID, ITS-scuId, StationID FROM CALMmanagement { iso (1) standard (0) calm-
management (24102) local (1) asnm-1 (1)}

TransportAddressType, TransportAddress FROM TRANSPORT-ADDRESS-MIB

;

-- End of IMPORTS

-- Types

-- PDUs --

-- SAM --

SAM::=SEQUENCE{
    fmtID          FmtID, -- value sam
    version        VersionFSAP,
    serverID       StationID,
    serviceList    ServiceList,
    channelList    ChannelList,
    ipServList     IpServList
}

FmtID::=INTEGER{
    sam (0),
    ctx (1)
} (0..15)

VersionFSAP::=INTEGER(0..15)

ServiceList::=SEQUENCE (SIZE(0..noNonipServices))OF NonipService

ChannelList::=SEQUENCE(SIZE(0..noChannels)) OF SessionChannel
-- Name changed from ServiceChannel to SessionChannel for clarification

IpServList::=SEQUENCE (SIZE(0..noIpServices))OF IpService

NonipService::=SEQUENCE{
    serviceID      ITSaid,
    serviceData    ServiceData,
    serverPort     PortNumber, -- always transmitted, even if not used
    sessionChannel INTEGER(0..noChannels) -- '0':no change of channel
}

SessionChannel::= SEQUENCE{
    serviceChannel INTEGER(0..255), -- medium-specific channel number
    medium          MedType, -- identification of access technology
    schParams       OCTET STRING -- medium-specific parameters
}

IpService::=SEQUENCE{
    serviceID      ITSaid,
    serviceData    IpServiceData,
    ipInfo         IpInfo,
    sessionChannel INTEGER(0..noChannels)
}

-- CTX --

CTX::=SEQUENCE{
    fmtID          FmtID, -- value ctx
    version        VersionFSAP,
    clientID       StationID,

```

```

servContextList      ServContextList,
ipContextList        IpContextList
}

ServContextList ::= SEQUENCE (SIZE(0..noNonipContexts)) OF NonipContext

IpContextList ::= SEQUENCE (SIZE(0..noIpContexts)) OF IpContext

IpContext ::= SEQUENCE{
    serviceID          ITSaid,
    contextData        IpContextData,
    ipInfo              IpInfo
}

-- MF-SAP services --

GCctxTxCmd ::= SEQUENCE{
    link  LLserviceAddr, -- NT protocol and UC-VCI
    ctx   CTX
}

GCperiodCmd ::= SEQUENCE{
    applicationID      ApplicationID,
    bcVCIs              SEQUENCE (SIZE(1..256)) OF LLserviceAddr,
    gcInterval          GcInterval, -- repetition interval
    priority             UserPriority, -- of advertisement
    serviceDataReg      ServiceDataReg -- advertisement details
}

GCsamctx ::= SEQUENCE{
    applicationID      ApplicationID, -- unique in the host
    serverID           StationID, -- of peer station
    serviceInfo        ServiceInfo,
    link                LLserviceAddr
}

GCsamctxConf ::= SEQUENCE{
    applicationID      ApplicationID, -- unique in the host
    link                LLserviceAddr, -- as received in the GCsamctx
    port                PortNumber -- dynamically assigned port number to be used in
    CTX
}

GCdeleteCmd ::= SEQUENCE{
    applicationID      ApplicationID
}

ServiceInfo ::= SEQUENCE{
    fill               BIT STRING (SIZE(7)),
    info               CHOICE{
        nonipService   NonipSAMctx,
        ipService       IpSAMctx
    }
}

NonipSAMctx ::= SEQUENCE{
    serviceID          ITSaid,
    providerPort       PortNumber
}

IpSAMctx ::= SEQUENCE{
    serviceID          ITSaid,
    ipInfo              IpInfo
}

-- MN-SAP services --

CTXrxNot ::= SEQUENCE{
    link  LLserviceAddr,
    ctx   CTX
}

```

```

SAMrxNot ::= SEQUENCE {
    link    LLserviceAddr,
    sam     SAM
}

GCsam ::= SEQUENCE {
    applicationID    ApplicationID, -- unique in the host
    serverID         StationID, -- peer station
    serviceData      SAMserviceData,
    link             LLserviceAddr
}

SAMserviceData ::= SEQUENCE {
    fill          BIT STRING (SIZE(7)),
    servData      CHOICE {
        nonipService NonipSAM,
        ipService     IpSAM
    }
}

NonipSAM ::= SEQUENCE {
    serviceID        ITSaid,
    serviceData      ServiceData,
    providerPort     PortNumber,
    sessionChannel   SessionChannel
}

IpSAM ::= SEQUENCE {
    serviceID        ITSaid,
    serviceData      IpServiceData,
    ipInfo           IpInfo,
    sessionChannel   SessionChannel
}

GCctx ::= SEQUENCE {
    applicationID    ApplicationID, -- unique in the host
    clientID         StationID, -- peer station
    serviceContext   CTXserviceData
}

CTXserviceData ::= SEQUENCE {
    fill          BIT STRING (SIZE(7)),
    servData      CHOICE {
        nonipContext NonipContext,
        ipContext     IpContext
    }
}

NonipContext ::= SEQUENCE {
    serviceID        ITSaid,
    contextData      ContextData,
    userPort         PortNumber
}

GCregerServer ::= SEQUENCE {
    applicationID    ApplicationID,
    gCschedule       GCschedule,
    priority         UserPriority,
    serviceDataReg   ServiceDataReg
}

GCupdateServer ::= SEQUENCE {
    applicationID    ApplicationID,
    gCschedule       GCschedule,
    fill             BIT STRING (SIZE(7)),
    serviceDataReg   SEQUENCE (SIZE(0..1)) OF ServiceDataReg
}

GCderegServer ::= SEQUENCE {
    applicationID    ApplicationID
}

```

```

GCreateClient ::= SEQUENCE {
    applicationID      ApplicationID,
    priority            UserPriority,
    serviceID          ITSaid,
    contextData        ContextData
}

GUpdateClient ::= SEQUENCE {
    applicationID      ApplicationID,
    serviceID          ITSaid,
    contextData        ContextData
}

GDeleteClient ::= SEQUENCE {
    applicationID      ApplicationID
}

GCreateServerConf ::= SEQUENCE {
    applicationID      ApplicationID
}

GUpdateServerConf ::= SEQUENCE {
    applicationID      ApplicationID
}

GDeleteServerConf ::= SEQUENCE {
    applicationID      ApplicationID
}

GCreateClientConf ::= SEQUENCE {
    applicationID      ApplicationID
}

GUpdateClientConf ::= SEQUENCE {
    applicationID      ApplicationID
}

GDeleteClientConf ::= SEQUENCE {
    applicationID      ApplicationID
}

-- General types --
ServiceData ::= OCTET STRING (SIZE(0..noServiceDataOctets))

ContextData ::= OCTET STRING (SIZE(0..noContextDataOctets))

IpServiceData ::= OCTET STRING (SIZE(0..noIpServiceDataOctets))

IpContextData ::= OCTET STRING (SIZE(0..noIpContextDataOctets))

GCSchedule ::= SEQUENCE (SIZE(0..255)) OF GCSched

GCSched ::= SEQUENCE {
    medium MedType,
    directivity Directivity,
    gcInterval GcInterval
}

ServiceDataReg ::= SEQUENCE {
    fill          BIT STRING (SIZE(7)),
    dataReg       CHOICE {
        nonipData [0] NonipServiceReg,
        ipData [1] IpServiceReg
    }
}

NonipServiceReg ::= SEQUENCE {
    serviceID     ITSaid,
    serviceData   OCTET STRING (SIZE(0..noServiceDataOctets)),

```